

# MODEL: PUZZLE-IN002

1U Network Appliance with 8th Gen. Intel® Core™ i7/i5/i3, Pentium® or Celeron® Processor, DDR4, Six GbE Ports, PCIe x16 Slot, M.2, Mini-SATA, Rack Mount, and RoHS

# **User Manual**



in little One

HOM THOUTHOROGICS

Rev. 1.01 - February 19, 2019



Date	Version	Changes
February 19, 2019	1.01	Updated internal system images
November 23, 2018	1.00	Initial release

# Copyright

Integration Corp.

### **COPYRIGHT NOTICE**

The information in this document is subject to change without prior notice in order to improve reliability, design and function and does not represent a commitment on the part of the manufacturer.

In no event will the manufacturer be liable for direct, indirect, special, incidental, or consequential damages arising out of the use or inability to use the product or documentation, even if advised of the possibility of such damages.

This document contains proprietary information protected by copyright. All rights are reserved. No part of this manual may be reproduced by any mechanical, electronic, or other means in any form without prior written permission of the manufacturer.

#### TRADEMARKS

All registered trademarks and product names mentioned herein are used for identification purposes only and may be trademarks and/or registered trademarks of their respective owners.

# **Manual Conventions**



Integration Corp.

### WARNING

Warnings appear where overlooked details may cause damage to the equipment or result in personal injury. Warnings should be taken seriously.



### CAUTION

Cautionary messages should be heeded to help reduce the chance of losing data or damaging the product.



### NOTE

These messages inform the reader of essential but non-critical information. These messages should be read carefully as any directions or instructions contained therein can help avoid making mistakes.

Page iv

# **Table of Contents**

EIntegration Corp.

1 INTRODUCTION	
1.1 Overview	
1.2 MODEL VARIATIONS	
1.3 Features	
1.4 Front Panel	
1.5 Rear Panel	
1.6 TECHNICAL SPECIFICATIONS	
1.7 DIMENSIONS	
2 UNPACKING	7
2.1 Anti-static Precautions	
2.2 UNPACKING PRECAUTIONS	
2.3 PACKING LIST	9
2.4 Optional Items	
3 INSTALLATION	11
3.1 INSTALLATION PRECAUTIONS	
3.2 TOP COVER REMOVAL	
3.3 DIMM INSTALLATION	
3.4 HDD INSTALLATION	
3.5 PCIE EXPANSION CARD INSTALLATION	
3.6 M.2 MODULE INSTALLATION	
3.7 MINI-SATA CARD INSTALLATION	
3.7.1 Half-size Card Installation	
3.8 LAN CONNECTION	
3.9 Console Connection	
3.10 Mounting the System	
3.11 POWER-ON PROCEDURE	
3.12 Available Drivers	
3.12.1 Driver Download	
	28

Page v

3.13.1 Clear CMOS	
3.13.2 Flash Descriptor Security Override Jumper	
4 BIOS	
4.1 Introduction	
4.1.1 Starting Setup	
4.1.2 Using Setup	
4.1.3 Getting Help	
4.1.4 Unable to Reboot after Configuration Changes	
4.1.5 BIOS Menu Bar	
4.2 MAIN	
4.3 Advanced	
4.3.1 CPU Configuration	
4.3.2 Trusted Computing	
4.3.3 iWDD H/W Monitor	
4.3.3.1 Smart Fan Mode Configuration	
4.3.4 IT8528 Super IO Configuration	
4.3.4.1 Serial Port 1 Configuration	
4.3.5 Serial Port Console Redirection	
4.3.5.1 Legacy Console Redirection Settings	
4.3.6 NVMe Configuration	
4.4 CHIPSET	
4.4.1 System Agent (SA) Configuration	
4.4.1.1 Memory Configuration	
4.4.1.2 Graphics Configuration	
4.4.1.3 PEG Port Configuration	50
4.4.2 PCH-IO Configuration	
4.4.2.1 SATA and RST Configuration	
4.4.2.2 HD Audio Configuration	53
4.5 Security	
4.6 Воот	55
4.7 Save & Exit	57
5 INTERFACE CONNECTORS	58
5.1 Peripheral Interface Connectors	59

5.2 INTERNAL PERIPHERAL CONNECTORS	60
5.2.1 ATX Power Connector (ATX1)	61
5.2.2 CPU Power Connector (CPU12V1)	61
5.2.3 Chassis Intrusion Connector (CHASSIS1)	61
5.2.4 DIO Connector (DIO1)	62
5.2.5 EC Debug Connector (CN1)	62
5.2.6 Fan Connectors (CPU_FAN1/2/3, SYS_FAN1)	62
5.2.7 Front Panel Connector (F_PANEL1)	63
5.2.8 LCM Connector (CN2)	63
5.2.1 M.2 Slot (M2_CN1)	64
5.2.2 Mini-SATA Card Slot (MINI_PCIE1)	65
5.2.1 Power Switch Connector (PWR_BTN1)	66
5.2.2 SATA Connector (SATA_SLOT1)	66
5.2.3 SPI Flash Connector (JSPI1)	67
5.2.4 SPI Flash Connector - EC (JSPI2)	67
5.2.5 TPM Connector (TPM1)	68
5.2.6 USB 2.0 Connector (USB1)	68
5.2.7 USB DOM Connector (USB_DOM1)	68
A REGULATORY COMPLIANCE	70
B SAFETY PRECAUTIONS	75
B.1 SAFETY PRECAUTIONS	76
B.1.1 General Safety Precautions	76
B.1.2 Anti-static Precautions	76
B.1.3 Product Disposal	77
B.2 MAINTENANCE AND CLEANING PRECAUTIONS	78
B.2.1 Maintenance and Cleaning	78
B.2.2 Cleaning Tools	78
C HAZARDOUS MATERIALS DISCLOSURE	80

Page vii



# List of Figures

Figure 1-1: PUZZLE-IN002 Series2
Figure 1-2: PUZZLE-IN002 Front Panel3
Figure 1-3: PUZZLE-IN002 Rear Panel4
Figure 1-4: Physical Dimensions (millimeters)6
Figure 3-1: Top Cover Removal13
Figure 3-2: DIMM Slot Locations14
Figure 3-3: HDD Bracket Retention Screws15
Figure 3-4: Secure HDD to the Bracket16
Figure 3-5: HDD Installation16
Figure 3-6: Expansion Slot Module Retention Screws17
Figure 3-7: Disconnect the Expansion Slot Module18
Figure 3-8: Blank Bracket Screw18
Figure 3-9: PCIe Expansion Card Installation19
Figure 3-10: Expansion Slot Module Installation20
Figure 3-11: Mini-SATA Slot Location22
Figure 3-12: RJ-45 Ethernet Connector23
Figure 3-13: Rack Mounting Bracket Installation25
Figure 3-14: Power-on
Figure 3-15: IEI Resource Download Center26
Figure 3-16: Clear CMOS Button Location29
Figure 3-17: Flash Descriptor Security Override Jumper Location

Page viii

# **List of Tables**

Table 1-1: PUZZLE-IN002 Model Variations	2
Table 1-2: Technical Specifications	6
Table 3-1: LAN Pinouts	23
Table 3-2: RJ-45 Ethernet Connector LEDs	23
Table 3-3: RJ-45 Serial Port Pinouts	24
Table 3-4: Flash Descriptor Security Override Jumper Settings	29
Table 4-1: BIOS Navigation Keys	33
Table 5-1: Peripheral Interface Connectors	60
Table 5-2: ATX Power Connector Pinouts	61
Table 5-3: CPU Power Connector (CPU12V1) Pinouts	61
Table 5-4: Chassis Intrusion Connector (CHASSIS1) Pinouts	61
Table 5-5: DIO Connector (DIO1) Pinouts	62
Table 5-6: EC Debug Connector (CN1) Pinouts	62
Table 5-7: Fan Connectors (CPU_FAN1/2/3, SYS_FAN1) Pinouts	62
Table 5-8: Front Panel Connector (F_PANEL1) Pinouts	63
Table 5-9: LCM Connector (CN2) Pinouts	63
Table 5-10: M.2 Slot (M2_CN1) Pinouts	65
Table 5-11: Mini-SATA Card Slot (MINI_PCIE1) Pinouts	66
Table 5-12: Power Switch Connector (PWR_BTN1) Pinouts	66
Table 5-13: SATA 6Gb/s Connector (SATA_SLOT1) Pinouts	67
Table 5-14: SPI Flash Connector (JSPI1) Pinouts	67
Table 5-15: SPI Flash Connector - EC (JSPI2) Pinouts	67
Table 5-16: TPM Connector (TPM1) Pinouts	68
Table 5-17: USB 2.0 Connector (USB1) Pinouts	68
Table 5-18: USB DOM Connector (USB_DOM1) Pinouts	69



Integration Corp.

# Introduction

f





# 1.1 Overview



#### Figure 1-1: PUZZLE-IN002 Series

The PUZZLE-IN002 is a 1 U network appliance series powered by the 8th generation Intel® Core<sup>™</sup> i7/i5/i3, Pentium® or Celeron® processor. It is optimized to host VNFs (Virtual Network Functions) and is ideal for SD-WAN.

The PUZZLE-IN002 supports six copper GbE ports for high-speed network applications, and it is equipped with a PCIe 3.0 x16 slot for upgrading with expansion cards, such as NIC cards or accelerator cards.

Multiple storage interfaces for fast and stable data transmission are offered through two SATA 6Gb/s connectors and one Mini-SATA slot that supports mSATA module.

## **1.2 Model Variations**

The model variations of the PUZZLE-IN002 are listed below.

Model No.	CPU	Memory	SSD
PUZZLE-IN002-PGT	Intel <sup>®</sup> Pentium <sup>®</sup> Gold G5400T preinstalled	N/A	N/A
PUZZLE-IN002-PGT/8GB	Intel <sup>®</sup> Pentium <sup>®</sup> Gold G5400T preinstalled	8 GB	256 GB
PUZZLE-IN002-i3T	Intel <sup>®</sup> Core™ i3-8100T preinstalled	N/A	N/A
PUZZLE-IN002-i3T/8GB	Intel <sup>®</sup> Core <sup>™</sup> i3-8100T preinstalled	8 GB	256 GB

Table 1-1: PUZZLE-IN002 Model Variations

## **1.3 Features**

The PUZZLE-IN002 features are listed below:

- Powered by 8th gen Intel<sup>®</sup> Core<sup>™</sup> i7/i5/i3, Pentium<sup>®</sup> or Celeron<sup>®</sup> processor
- Support two 2400 MHz DDR4 non-ECC RDIMMs (system max. 32 GB)
- Support two 2.5" SATA SSD/HDD
- Support up to six GbE connections via Intel® I211 controllers
- Upgradable with future expansion cards by one PCIe 3.0 x16 slot, one M.2 slot and one Mini-SATA card slot
- One RJ-45 RS-232 serial port
- Supports two USB 3.1 Gen 1 (5 Gb/s) ports
- 1U chassis for rack mounting
- RoHS compliant

## **1.4 Front Panel**

The overview of the front panel is shown in **Figure 1-2**.



#### Figure 1-2: PUZZLE-IN002 Front Panel

The states of the LED indicators located on the front panel are listed below.

	Off	The system is turned off.
Power LED	Blue	The system is turned on.
	Off	No HDD activity
HDD Status LED	Blinking Blue	HDD activity
	Off	No alert
Alert LED	Red	Alert message





# 1.5 Rear Panel

An overview of the PUZZLE-IN002 rear panel is shown in **Figure 1-3** below.



Figure 1-3: PUZZLE-IN002 Rear Panel

# **1.6 Technical Specifications**

The PUZZLE-IN002 technical specifications are listed below.

System		
Form Factor	1U	
CPU (SoC)	8 <sup>th</sup> gen Intel <sup>®</sup> Core™ i7, i5, i3, Pentium <sup>®</sup> or Celeron <sup>®</sup> processor	
	<b>PGT SKU:</b> 8 <sup>th</sup> gen Intel <sup>®</sup> Pentium <sup>®</sup> Gold G5400T processor	
	i3T SKU: 8 <sup>th</sup> gen Intel <sup>®</sup> Core™ i3-8100T processor	
Chipset	Intel <sup>®</sup> H310	
Memory	Two 288-pin 2400 MHz DDR4 non-ECC RDIMM slots	
	(system max. 32 GB)	
	(8G SKUs are pre-installed with two 4 GB memory modules)	
Networking	Intel <sup>®</sup> I211-AT Ethernet controller	
	6 x Copper 1GbE LAN port	
Network Acceleration	Intel® AES New Instructions	
and Security	Intel® Software Guard Extensions (Intel® SGX)	
	Intel® Memory Protection Extensions (Intel® MPX)	
	Intel® Trusted Execution Technology	
Storage	2 x 2.5" SATA 6Gb/s HDD/SSD bay	



USB DOM	1 x USB DOM (internal)	
QTS	QTS Gateway security	
Expansion		
PCle	1 x PCle 3.0 x16 slot	
Mini-SATA	1 x Mini-SATA slot (reserved for WWAN module, supports SATA and USB 2.0 signals)	
M.2	1 x M.2 A-key 2230 slot (reserved for Wi-Fi module, supports PCIe and USB 2.0 signals)	
I/O and Indicators		
Console	1 x RJ-45 RS-232	
USB	2 x USB 3.1 Gen 1 (5 Gb/s) port (external)	
	2 x USB 2.0 internal pin-header (8-pin, p=2.54)	
Indicator	LCM (with two control buttons)	
	Power status (blue)	
	HDD status (green)	
	Alert LED (programmable, red)	
Switch/Button	Power switch (rear panel)	
	Reset button (front panel)	
ТРМ	1 x TPM 2.0 (2x10 pin header)	
Antenna Connector	1 x Knockout hole for antenna connector	
Power		
Power Input	100 V ~ 240 V	
	ATX power, 240 W	
Thermal Solution	1 x Passive heatsink for CPU	
	3 x Smart fan for CPU	
	1 x Smart fan for system	
Environmental and Mechanical		
Mounting	1U rack mount	
Operating	0°C~40°C (32°F~104°F)	
Temperature		

Page 5

Storage Temperature	-10°C~50°C (14°F~122°F)
Operating Humidity	5%~90%, non-condensing
Safety	CE, FCC
Weight	5 kg
Physical Dimensions	430 mm x 320 mm x 44.2 mm (W x D x H)
Operating System	Linux Ubuntu 16.04

 Table 1-2: Technical Specifications

# **1.7 Dimensions**

The physical dimensions are shown below:





Figure 1-4: Physical Dimensions (millimeters)



EnIntegration Corp.

# Unpacking



## 2.1 Anti-static Precautions



Failure to take ESD precautions during installation may result in permanent damage to the PUZZLE-IN002 and severe injury to the user.

Electrostatic discharge (ESD) can cause serious damage to electronic components, including the PUZZLE-IN002. Dry climates are especially susceptible to ESD. It is therefore critical that whenever the PUZZLE-IN002 or any other electrical component is handled, the following anti-static precautions are strictly adhered to.

- *Wear an anti-static wristband*: Wearing a simple anti-static wristband can help to prevent ESD from damaging the board.
- Self-grounding: Before handling the board, touch any grounded conducting material. During the time the board is handled, frequently touch any conducting materials that are connected to the ground.
- Use an anti-static pad: When configuring the PUZZLE-IN002, place it on an anti-static pad. This reduces the possibility of ESD damaging the PUZZLE-IN002.

## **2.2 Unpacking Precautions**

When the PUZZLE-IN002 is unpacked, please do the following:

- Follow the anti-static precautions outlined in Section 2.1.
- Make sure the packing box is facing upwards so the PUZZLE-IN002 does not fall out of the box.
- Make sure all the components shown in Section 2.3 are present.

# 2.3 Packing List



If some of the components listed in the checklist below are missing, please do not proceed with the installation. Contact the IEI reseller or vendor you purchased the PUZZLE-IN002 from or contact an IEI sales representative directly. To contact an IEI sales representative, please send an email to <u>sales@ieiworld.com</u>.

The PUZZLE-IN002 is shipped with the following components:

Quantity	Item	Image
1	PUZZLE-IN002	
1	Power cord	
2	Rack mounting bracket	
6	Mounting bracket screw (M4*6)	*
10	Screw for securing HDD (M3*4)	
1	USB to console cable (only for SKUs with memory)	

Page 9

Quantity	Item	Image
1	RS-232 to console cable (only for SKUs without memory)	

# 2.4 Optional Items

The following table lists the optional items that can be purchased separately.

Optional Item	Image
Slide rail	
( <b>P/N</b> : RAIL-B02)	
USB to console cable	
( <b>P/N</b> : 32013-004000-100-RS)	
RS-232 to console cable	
( <b>P/N</b> : 32005-005100-100-RS)	
20-pin Infineon TPM 2.0 module, software	
management tool, firmware v5.5	
( <b>P/N</b> : TPM-IN02-R20)	





EnIntegration Corp.

# Installation



## **3.1 Installation Precautions**

Integration Corp.

During installation, be aware of the precautions below:

- Read the user manual: The user manual provides a complete description of the PUZZLE-IN002, installation instructions and configuration options.
- DANGER! Disconnect Power: Power to the PUZZLE-IN002 must be disconnected during the installation process. Failing to disconnect the power may cause severe injury to the body and/or damage to the system.
- Qualified Personnel: The PUZZLE-IN002 must be installed and operated only by trained and qualified personnel. Maintenance, upgrades, or repairs may only be carried out by qualified personnel who are familiar with the associated dangers.
- Air Circulation: Make sure there is sufficient air circulation when installing the PUZZLE-IN002. The PUZZLE-IN002's cooling vents must not be obstructed by any objects. Blocking the vents can cause overheating of the PUZZLE-IN002. Leave at least 5 cm of clearance around the PUZZLE-IN002 to prevent overheating.
- Grounding: The PUZZLE-IN002 should be properly grounded. The voltage feeds must not be overloaded. Adjust the cabling and provide external overcharge protection per the electrical values indicated on the label attached to the back of the PUZZLE-IN002.

## 3.2 Top Cover Removal

Before installing or maintaining the internal components, the top cover must be removed from the PUZZLE-IN002. Follow the steps below to complete the task.

- Step 1: Remove the four retention screws indicated in Figure 3-1.
- Step 2: Slide the top cover towards the rear side and gently lift the top cover (Figure 3-1).



Figure 3-1: Top Cover Removal

## **3.3 DIMM Installation**



For dual channel configuration, always install two identical memory modules that feature the same capacity, timings, voltage, number of ranks and the same brand.

To install the DIMM module, please follow the steps below.

- Step 1: Remove the top cover from the PUZZLE-IN002. Please follow the instruction described in Section 3.2.
- Step 2: Locate the DIMM slots on the motherboard.



Figure 3-2: DIMM Slot Locations

- **Step 3:** Open the DIMM socket handles. Open the two handles outwards as far as they can.
- **Step 4:** Align the DIMM so the notch on the memory lines up with the notch on the memory socket.
- **Step 5:** Once aligned, press down until the DIMM is properly seated. Clip the two handles into place.
- **Step 6:** To remove a DIMM, push both handles outward. The memory module is ejected by a mechanism in the socket.

# **3.4 HDD Installation**

The PUZZLE-IN002 allows installation of two 2.5" SATA HDD/SSD. To install HDDs into the system, please follow the steps below.

- Step 1: Remove the top cover from the PUZZLE-IN002. Please follow the instruction described in Section 3.2.
- Step 2: Remove the HDD bracket from the system. To do this, remove the three retention screws indicated below and disconnect the SATA connector module from the motherboard.



Figure 3-3: HDD Bracket Retention Screws

**Step 3:** Insert an HDD into the bracket until the HDD is properly connected to the SATA connector. Secure the HDD with four retention screws (M3\*4). See **Figure 3-5**.





Figure 3-4: Secure HDD to the Bracket

**Step 4:** Re-connect the SATA connector module to the motherboard. Secure the bracket to the chassis with three screws removed previously (**Figure 3-5**).



Figure 3-5: HDD Installation

**Step 5:** Re-install and secure the top cover to the system.



## 3.5 PCIe Expansion Card Installation

The PUZZLE-IN002 allows installation of one PCIe x16 card. To install a PCIe expansion card, please follow the steps below.

- Step 1: Remove the top cover from the PUZZLE-IN002 (refer to Section 3.2).
- Step 2: Remove the four expansion slot module retention screws indicated below.



Figure 3-6: Expansion Slot Module Retention Screws





**Step 3:** Push the expansion slot module with strength to disconnect the module from the edge connector of the motherboard.



Figure 3-7: Disconnect the Expansion Slot Module

**Step 4:** Remove the blank bracket panel that aligns with the PCIe slot for installing the expansion card. Save the bracket screw.



Figure 3-8: Blank Bracket Screw

Page 18

**Step 5:** Align the expansion card to the PCIe slot. Press gently, but firmly, to seat the expansion card correctly in the slot. Install the bracket screw to secure the card to the expansion slot module.



#### Figure 3-9: PCIe Expansion Card Installation

Step 6: Place the expansion slot module back to the original position by hooking the slotted hole into the positioning stud in the chassis (Figure 3-10 A). Push the connector of the expansion slot module into the edge connector to install it. During installation, ensure that

1. the connector on the slot module is properly aligned and connected to the edge connector;

- 2. the two studs on the side is going through the two holes in the chassis;
- 3. the slot module tab is going under the chassis tab.







#### Figure 3-10: Expansion Slot Module Installation

- Step 7: Secure the expansion slot module with the four retention screws previously removed.
- Step 8: Re-install the top cover.

# 3.6 M.2 Module Installation

The M.2 slot is keyed in the A position and provides mounting screw position for 2230-size M.2 module. To install an M.2 module, please follow the steps below.

Step 1: Remove the top cover from the PUZZLE-IN002. See Section 3.2.

**Step 2:** Locate the M.2 slot on the motherboard.







- Step 3: Remove the on-board retention screw.
- **Step 4:** Line up the notch on the module with the notch on the slot. Slide the M.2 module into the socket at an angle of about 20°.
- Step 5: Push the M.2 module down and secure it with the previously removed retention screw.

## 3.7 Mini-SATA Card Installation

The PUZZLE-IN002 has one full-size/half-size Mini-SATA slot on the motherboard. To install a full-size module, follow the instructions below.

- **Step 1:** Remove the top cover from the PUZZLE-IN002. See **Section 3.2**.
- Step 2: Locate the Mini-SATA slot on the motherboard (Figure 3-11).





#### Figure 3-11: Mini-SATA Slot Location

- Step 3: Remove the pre-installed retention screw from the standoff.
- Step 4: Line up the notch on the card with the notch on the slot. Slide the card into the socket at an angle of about 20°.
- Step 5: Secure the full-size card with the retention screw previously removed.

### 3.7.1 Half-size Card Installation

The Mini-SATA slot also allows installation of a half-size Mini-SATA card. To install a half-size card, please follow the steps below.

- Step 1: Remove the pre-installed retention screw and the standoff from the motherboard.
- Step 2: Install the previously removed standoff to the screw hole for the half-size Mini-SATA card.
- Step 3: Line up the notch on the card with the notch on the slot. Slide the card into the socket at an angle of about 20°.
- **Step 4:** Secure the half-size card with the retention screw previously removed.





# **3.8 LAN Connection**

The LAN connectors on the front panel allow connection to an external network. The pinouts of the LAN connectors are listed below.

Pin	Description	Pin	Description
1	TRD0+	5	TRD2-
2	TRD0-	6	TRD1-
3	TRD1+	7	TRD3+
4	TRD2+	8	TRD3-

Table 3-1: LAN Pinouts



Figure 3-12: RJ-45 Ethernet Connector

The RJ-45 Ethernet connector has two status LEDs, one yellow and one green/orange. The yellow LED indicates activity on the port and the green/orange LED indicates the speed. See **Table 3-2**.

Activity/Link LED		Speed LED	
STATUS	DESCRIPTION	STATUS	DESCRIPTION
Off	No link	Off	10 Mbps connection
Yellow	Linked	Green	100 Mbps connection
Blinking	TX/RX activity	Orange	1 Gbps connection

Table 3-2: RJ-45 Ethernet Connector LEDs

# **3.9 Console Connection**

The PUZZLE-IN002 has one RJ-45 serial device connector on the front panel. The RJ-45 connector for the serial port can be identified easily as the RJ-45 for the network has two LEDs on the port, while the connectors for the serial cables don't. The pinouts of the serial port are listed below.

Pin	Description	Pin	Description
1	-NRTS1	5	GND
2	-NDTR1	6	NSIN1
3	NSOUT1	7	-NDSR1
4	GND	8	-NCTS1

Table 3-3: RJ-45 Serial Port Pinouts

The serial device slot (RJ-45) connects to a cable with a standard D-sub 9 connector or a USB connector (varied from SKU) at the other end.



## 3.10 Mounting the System

The PUZZLE-IN002 is shipped with two mounting brackets that support 1U rack mount. To install the mounting brackets, please follow the steps below.

- **Step 1:** Align the three retention screw holes in each bracket with the corresponding retention screw holes on the sides of the PUZZLE-IN002.
- Step 2: Secure the brackets to the system by inserting three retention screws (M4\*6) into each bracket (Figure 3-13). Make sure the screws are tight and on the right positions.





Figure 3-13: Rack Mounting Bracket Installation

## 3.11 Power-On Procedure



Make sure a power supply with the correct input voltage is being fed into the system. Incorrect voltages applied to the system may cause damage to the internal electronic components and may also cause injury to the user.

To power-on the PUZZLE-IN002 please follow the steps below:

- Step 1: Connect the power source to the power inlet on the rear panel.
- Step 2: Turn on the power switch to power up the system.
- Step 3: The power LED indicator on the front panel turns to green.





Figure 3-14: Power-on

## 3.12 Available Drivers

All the drivers for the PUZZLE-IN002 are available on IEI Resource Download Center (<u>https://download.ieiworld.com</u>). Type PUZZLE-IN002 and press Enter to find all the relevant software, utilities, and documentation.



Figure 3-15: IEI Resource Download Center



To install software from the downloaded ISO image file in Windows 10, double-click the ISO file to mount it as a virtual drive to view its content.


## 3.12.1 Driver Download

To download drivers from IEI Resource Download Center, follow the steps below.

Step 1: Go to <u>https://download.ieiworld.com</u>. Type PUZZLE-IN002 and press Enter.



Step 2: All product-related software, utilities, and documentation will be listed. You can choose **Driver** to filter the result.

All Type BIOS Datasheet	Driver	SDK	User Manual Utility	Others
WAFER-BT-i1				Product Info 🕨
♣ Embedded Computer ▶ Single Board Computer ▶ Embedded Board				
3.5" SBC with Intel® 22nm Atom Im/Celeron® on-t	board Soc			
File Name	Published	Version	File Checksur	n
7B000-001033-RS V2.3.iso (2.23 GB)	2017/10/03	2.30	3B2DB1F792779A93A8F50DE	DBC3943E30

Step 3: Click the driver file name on the page and you will be prompted with the following window. You can download the entire ISO file (●), or click the small arrow to find an individual driver and click the file name to download (●).

Integration Corp.



## 3.13 Maintenance

To configure the jumper settings, please follow the steps below.

- Step 1: Remove the top cover. See Section 3.2.
- Step 2: Locate the jumper/button on the embedded motherboard.
- **Step 3:** Make the jumper settings in accordance with the settings described and defined in the following sections.

## 3.13.1 Clear CMOS

If the PUZZLE-IN002 fails to boot due to improper BIOS settings, the clear CMOS button clears the CMOS data and resets the system BIOS information. To do this, push the clear CMOS button for a few seconds.

If the "CMOS Settings Wrong" message is displayed during the boot up process, the fault may be corrected by pressing the F1 to enter the CMOS Setup menu. Do one of the following:

- Enter the correct CMOS setting
- Load Optimal Defaults
- Load Failsafe Defaults.

Page 28

After having done one of the above, save the changes and exit the CMOS Setup menu.

Integration Corp.

The clear CMOS button location is shown in Figure 3-16 below.



Figure 3-16: Clear CMOS Button Location

#### 3.13.2 Flash Descriptor Security Override Jumper

The Flash Descriptor Security Override jumper (J\_FLASH1) allows users to enable or disable the ME firmware update. Refer to **Figure 3-17** and **Table 3-4** for the jumper location and settings.

Setting	Description
Short 1-2	Disabled (default)
Short 2-3	Enabled





Figure 3-17: Flash Descriptor Security Override Jumper Location

To update the ME firmware, please follow the steps below.

- **Step 1:** Before turning on the system power, short pin 2-3 of the jumper.
- Step 2: Update the BIOS and ME firmware, and then turn off the system power.
- Step 3: Remove the metal clip on the jumper or return to its default setting (short pin 1-2).
- Step 4: Restart the system. The system will reboot 2~3 times to complete the ME firmware update.









## **4.1 Introduction**

The BIOS is programmed onto the BIOS chip. The BIOS setup program allows changes to certain system settings. This chapter outlines the options that can be changed.



Some of the BIOS options may vary throughout the life cycle of the product and are subject to change without prior notice.

## 4.1.1 Starting Setup

The UEFI BIOS is activated when the computer is turned on. The setup program can be activated in one of two ways.

- 1. Press the DEL or F2 key as soon as the system is turned on or
- 2. Press the **DEL** or **F2** key when the "**Press DEL or F2 to enter SETUP**" message appears on the screen.

If the message disappears before the **DEL or F2** key is pressed, restart the computer and try again.

## 4.1.2 Using Setup

Use the arrow keys to highlight items, press **ENTER** to select, use the PageUp and PageDown keys to change entries, press **F1** for help and press **Esc** to quit. Navigation keys are shown in **Table 4-1**.

Кеу	Function
Up arrow	Move to previous item
Down arrow	Move to next item
Left arrow	Move to the item on the left hand side
Right arrow	Move to the item on the right hand side
+	Increase the numeric value or make changes





Кеу	Function	
-	Decrease the numeric value or make changes	
Esc key	Main Menu – Quit and not save changes into CMOS	
	Status Page Setup Menu and Option Page Setup Menu	
	Exit current page and return to Main Menu	
F1 key	General help, only for Status Page Setup Menu and Option	
	Page Setup Menu	
F2 key	Load previous values	
F3 key	Load optimized defaults	
F4 key	Save changes and exit BIOS	

**Table 4-1: BIOS Navigation Keys** 

## 4.1.3 Getting Help

When **F1** is pressed a small help window describing the appropriate keys to use and the possible selections for the highlighted item appears. To exit the Help Window press **Esc** or the **F1** key again.

## 4.1.4 Unable to Reboot after Configuration Changes

If the computer cannot boot after changes to the system configuration is made, CMOS defaults. Use the clear CMOS button described in **Chapter 3**.

## 4.1.5 BIOS Menu Bar

The menu bar on top of the BIOS screen has the following main items:

- Main Changes the basic system configuration.
- Advanced Changes the advanced system settings.
- Chipset Changes the chipset settings.
- Security Sets User and Supervisor Passwords.
- Boot Changes the system boot configuration.
- Save & Exit Selects exit options and loads default settings



The following sections completely describe the configuration options found in the menu items at the top of the BIOS screen and listed above.

# 4.2 Main

The **Main** BIOS menu (**BIOS Menu 1**) appears when the **BIOS Setup** program is entered. The **Main** menu gives an overview of the basic system information.

Aptio Setup Utility - Main Advanced Chipset	Copyright (C) 2018 America Security Boot Save	n Megatrends, Inc. & Exit
BIOS Information BIOS Vendor Core Version Compliancy Project Version Build Date and Time iWDD Vendor iWDD Version	American Megatrends 5.13 UEFI 2.6; PI 1.4 Z533AR12.BIN 09/12/2018 15:44:24 iEi Z533ER11.bin	Set the Date. Use Tab to switch between Date elements.
Processor Information Name Brand String Frequency ID Stepping Number of Processors Microcode Revision GT Info IGFX VBIOS Version Memory RC Version Total Memory Memory Frequency	CoffeeLake DT Intel(R) Core(TM) i3-8100T CPU @ 3.10GHz 3100 MHz 0x906EB B0 4Core(s) / 4Thread(s) 8E GT2 (0x3E91) 1010 0.7.1.58 8192 MB 2400 MHz	<pre>→←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
PCH Information Name PCH SKU Stepping	CNL PCH-H H310 B0	
ME FW Version ME Firmware SKU	12.0.0.1069 Consumer SKU	
Access Level	Administrator	
System Date System Time	[Thu 10/15/2018] [06:10:27]	
Version 2.20.1271. C	opvright (C) 2018 American	Megatrends, Inc.

**BIOS Menu 1: Main** 

Page 34

The Main menu has two user configurable fields:

#### ➔ System Date [xx/xx/xx]

Use the **System Date** option to set the system date. Manually enter the day, month and year.

#### ➔ System Time [xx:xx:xx]

Use the **System Time** option to set the system time. Manually enter the hours, minutes and seconds.

## 4.3 Advanced

Use the **Advanced** menu (**BIOS Menu 2**) to configure the CPU and peripheral devices through the following sub-menus:



Setting the wrong values in the sections below may cause the system to malfunction. Make sure that the settings made are compatible with the hardware.

	Apt Main	io Setup Ut Advanced	tility - ( Chipset	Copyright (C) Security	2018 Boot	America: Save	n Megatrends, Inc. & Exit
^ ^ ^ ^ ^ ^ ^	CPU Con Trusted iWDD H/ IT8528 Serial NVMe Co	figuration Computing M Monitor Super IO Co Port Conso onfiguration	onfigurati le Redirec n	ion ction			Trusted Computing Settings →←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit
	Ve	ersion 2.20	.1271. Co	pyright (C) 2	2018 An	nerican	Megatrends, Inc.

**BIOS Menu 2: Advanced** 

Page 35

## 4.3.1 CPU Configuration

Use the **CPU Configuration** menu (**BIOS Menu 3**) to view detailed CPU specifications or enable the Intel Virtualization Technology.

Aptio Setup Utility - Copyright (C) 2018 American Megatrends, Inc. Advanced			
CPU Configuration		When enabled, a VMM can utilize the additional	
Туре	Intel(R) Core(TM) i3-8100T CPU @ 3.10GHz	hardware capabilities provided by Vanderpool	
ID	0x906EB	Technology.	
Speed	3100 MHz		
L1 Data Cache	32 kB x 4		
L1 Instruction Cache	32 kB x 4		
L2 Cache	256 kB x 4		
L3 Cache	6 MB	$\rightarrow \leftarrow$ : Select Screen	
L4 Cache	N/A	$\uparrow \downarrow$ : Select Item	
VMX	Supported	Enter: Select	
SMX/TXT	Not Supported	+/-: Change Opt.	
		F1: General Help	
Intel (VMX) Virtualization	[Enabled]	F2: Previous Values	
Technology		F3: Optimized Defaults	
Active Processor Cores	[A11]	F4: Save & Exit	
		ESC: Exit	
Version 2.20.1271. Copyr	right (C) 2018 American	Megatrends, Inc.	

**BIOS Menu 3: CPU Configuration** 

#### → Intel (VMX) Virtualization Technology [Enabled]

Use the Intel (VMX) Virtualization Technology option to enable or disable virtualization on the system. When combined with third party software, Intel® Virtualization technology allows several OSs to run on the same system at the same time.

→	Disabled	Disables Intel Virtualization Technology.
---	----------	---

Enabled DEFAULT Enables Intel Virtualization Technology.

#### ➔ Active Processor Cores [All]

Use the **Active Processor Cores** BIOS option to enable numbers of cores in the processor package.

All **DEFAULT** Enable all cores in the processor package.



I Integration Corp.

## PUZZLE-IN002

→	1	Enable one core in the processor package.
→	2	Enable two cores in the processor package.
→	3	Enable three cores in the processor package.

## 4.3.2 Trusted Computing

Use the **Trusted Computing** menu (**BIOS Menu 4**) to configure settings related to the Trusted Computing Group (TCG) Trusted Platform Module (TPM).

Aptio Setup Utility - Copyright (C) 2018 America Advanced	n Megatrends, Inc.
Configuration Security Device Support [Disable] NO Security Device Found	Enables or Disables BIOS support for security device. O.S. will not show Security Device. TCG EFI protocol and INT1A interface will not be available.
	<pre>→←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>

**BIOS Menu 4: Trusted Computing** 

#### → Security Device Support [Disable]

Use the **Security Device Support** option to configure support for the TPM.

- → **Disable DEFAULT** TPM support is disabled.
- → Enable TPM support is enabled.



## 4.3.3 iWDD H/W Monitor

The **iWDD H/W Monitor** menu (**BIOS Menu 5**) contains the fan configuration submenu, and displays the system temperature and CPU fan speed.

Aptio Setup Utility - Copy	right (C) 2018 America	n Megatrends, Inc.
Advanced		
PC Health Status		Smart Fan Mode Select
CPU temperature	:+41 °C	
System temperature	:+29 °C	→←: Select Screen
CPU_FAN1 Speed CPU_FAN2 Speed CPU_FAN3 Speed SYS FAN1 Speed	:3422 RPM :3546 RPM :3276 RPM :N/A	<pre>↑↓: Select Item Enter: Select +/-: Change Opt. El: Conoral Walp</pre>
CPU_CORE +5V +12V +DDR +5VSB +3.3V +3.3VSB	:+0.953 V :+4.994 V :+12.225 V :+1.196 V :+5.052 V :+3.357 V :+3.311 V	F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit
> Smart Fan Mode Configuration		
Version 2.20.1271. Copyr:	ight (C) 2018 American	Megatrends, Inc.

**BIOS Menu 5: iWDD H/W Monitor** 

#### → PC Health Status

The following system parameters and values are shown. The system parameters that are monitored are:

- System Temperatures:
  - O CPU temperature
  - O System temperature
- Fan Speeds:
  - O CPU fan speed
  - O System fan speed
- Voltages:
  - O CPU\_CORE

Page 38



0	+5V

O +12V

- O DDR
- O +5VSB
- 0 +3.3V
- O +3.3VSB

## 4.3.3.1 Smart Fan Mode Configuration

Use the Smart Fan Mode Configuration submenu (BIOS Menu 6) to configure the CPU/system fan temperature and speed settings.

Integration Corp.

Page 39

Aptio Setup Utility - Copy	right (C) 2018 America	n Megatrends, Inc.
Advanced		
Smart Fan Mode Configuration		Smart Fan Mode Select
CPU_FAN1 Smart Fan Control Auto mode fan start temperature Auto mode fan off temperature Auto mode fan start PWM Auto mode fan slope PWM	[Auto Mode] 65 50 30 2	<pre>→←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt.</pre>
CPU_FAN2 Smart Fan Control Auto mode fan start temperature Auto mode fan off temperature Auto mode fan start PWM Auto mode fan slope PWM	[Auto Mode] 65 50 30 2	<pre>F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271. Copyri	ght (C) 2018 American	Megatrends, Inc.

**BIOS Menu 6: Smart Fan Mode Configuration** 

#### → CPU\_FAN Smart Fan Control [Auto Mode]

Use the CPU\_FAN Smart Fan Control options to configure the CPU Smart Fans.

→	Manual Mode		The fan spins at the speed set in Manual Mode
			settings.
→	Auto Mode	DEFAULT	The fan adjusts its speed using Auto Mode
			settings.

The following options can only be set if the CPU Smart Fan Control option is set to Auto Mode.

#### → Auto mode fan start temperature

If the CPU temperature is between **fan off** and **fan start**, the fan speed change to **fan start PWM**. To set a value, Use the + or - key to change the value or enter a decimal number between 1 and 100.

#### → Auto mode fan off temperature

If the CPU temperature is lower than the value set this option, the fan speed change to be lowest. To set a value, Use the + or - key to change the value or enter a decimal number between 1 and 100.

#### ➔ Auto mode fan start PWM

Use the **Auto mode fan start PWM** option to set the PWM start value. Use the + or - key to change the value or enter a decimal number between 1 and 100.

#### → Auto mode fan slope PWM

Use the **Auto mode fan slope PWM** option to select the linear rate at which the PWM mode increases with respect to an increase in temperature. Use the + or - key to change the value or enter a decimal number between 1 and 8.



## 4.3.4 IT8528 Super IO Configuration

Use the **IT8528 Super IO Configuration** menu (**BIOS Menu 7**) to set or change the configurations for the parallel ports and serial ports.

Aptio Setup Utility - Copyright (C) 2018 America Advanced	n Megatrends, Inc.
Super IO Configuration Super IO Chip IT8528	Set Parameters of Serial Port 1 (COMA)
> Serial Port 1 Configuration	<pre>→←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271. Copyright (C) 2018 American	Megatrends, Inc.

BIOS Menu 7: IT8528 Super IO Configuration

## 4.3.4.1 Serial Port 1 Configuration

Use the Serial Port 1 Configuration menu (BIOS Menu 8) to configure the serial port n.

Aptio Setup Utility - Copy Advanced	yright (C) 2018 America	n Megatrends, Inc.
Serial Port n Configuration		Enable or Disable Serial Port (COM)
Serial Port Device Settings	[Enabled] IO=3F8h; IRQ=4	
		<pre>→←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271. Copyr	right (C) 2018 American	Megatrends, Inc.

BIOS Menu 8: Serial Port 1 Configuration Menu



#### Serial Port [Enabled]

Use the Serial Port option to enable or disable the serial port.

→	Disabled	Disable the serial port

Enabled DEFAULT Enable the serial port

## 4.3.5 Serial Port Console Redirection

The **Serial Port Console Redirection** menu (**BIOS Menu 9**) allows the console redirection options to be configured. Console redirection allows users to maintain a system remotely by re-directing keyboard input and text output through the serial port.

Aptio Setup Utility - Copyright (C) 2018 America Advanced	n Megatrends, Inc.
COM1 Console Redirection [Disabled] > Console Redirection Settings	Console Redirection Enable or Disable
Legacy Console Redirection > Legacy Console Redirection Settings	<pre>→ ←: Select Screen ↑ ↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271. Copyright (C) 2018 American	Megatrends, Inc.

**BIOS Menu 9: Serial Port Console Redirection** 

#### ➔ Console Redirection [Enabled]

Use Console Redirection option to enable or disable the console redirection function.

- Disabled
   Disabled the console redirection function
- Enabled DEFAULT Enabled the console redirection function

The following options are available in the **Console Redirection Settings** submenu when the **Console Redirection** option is enabled.



#### ➔ Terminal Type [ANSI]

Use the **Terminal Type** option to specify the remote terminal type.

→	VT100		The target terminal type is VT100
→	VT100+		The target terminal type is VT100+
→	VT-UTF8		The target terminal type is VT-UTF8
→	ANSI	DEFAULT	The target terminal type is ANSI

#### → Bits per second [115200]

Use the **Bits per second** option to specify the serial port transmission speed. The speed must match the other side. Long or noisy lines may require lower speeds.

→	9600		Sets the serial port transmission speed at 9600.
→	19200		Sets the serial port transmission speed at 19200.
→	57600		Sets the serial port transmission speed at 57600.
→	115200	DEFAULT	Sets the serial port transmission speed at 115200.

#### → Data Bits [8]

Use the Data Bits option to specify the number of data bits.

→	7		Sets the data bits at 7.
→	8	DEFAULT	Sets the data bits at 8.

#### → Parity [None]

Use the **Parity** option to specify the parity bit that can be sent with the data bits for detecting the transmission errors.

→	None	DEFAULT	No parity bit is sent with the data bits.
→	Even		The parity bit is 0 if the number of ones in the data
			bits is even.



# Integration Corp.

## PUZZLE-IN002

<b>→</b>	Odd	The parity bit is 0 if the number of ones in the data bits is odd.
<b>→</b>	Mark	The parity bit is always 1. This option does not provide error detection.
<b>→</b>	Space	The parity bit is always 0. This option does not provide error detection.

## → Stop Bits [1]

Use the **Stop Bits** option to specify the number of stop bits used to indicate the end of a serial data packet. Communication with slow devices may require more than 1 stop bit.

→	1	DEFAULT	Sets the number of stop bits at 1.
→	2		Sets the number of stop bits at 2.

## 4.3.5.1 Legacy Console Redirection Settings

Aptio Setup Utility - Copyright (C) 2018 Am	merican Megatrends, Inc.
Advanced	
Legacy Serial Redirection Port [COM1]	Select a COM port to display redirection of Legacy OS and Legacy OPROM Messages.
Vergion 2 20 1271 Convright (C) 2018 Ame	<pre>→ ←: Select Screen ↑ ↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
version 2.20.1271. Copyright (C) 2018 Ame	rican Megatrends, Inc.

#### **BIOS Menu 10: Legacy Console Redirection Settings**

#### → Legacy Serial Redirection Port [COM1]

Use the **Legacy Serial Redirection Port** option to select a COM port to display redirection of legacy OS and legacy OPROM messages. Configuration option is listed below.

COM1 Default

## 4.3.6 NVMe Configuration

Use the **NVMe Configuration** (**BIOS Menu 11**) menu to display the NVMe controller and device information.

Advanced	
NVMe Configuration	
No NVMe Device Found	
→←: Select Screen	
↑↓: Select Item	
Enter: Select	
F1: General Help	
F2: Previous Valu	es
F3: Optimized Defa	aults
F4: Save & Exit	
Version 2 20 1271 Convright (C) 2018 American Megatrends Inc.	

**BIOS Menu 11: NVMe Configuration** 



# 4.4 Chipset

Use the **Chipset** menu (**BIOS Menu 12**) to access the PCH IO and System Agent (SA) configuration menus.

# 

Setting the wrong values for the Chipset BIOS selections in the Chipset BIOS menu may cause the system to malfunction.

	Apt Main	io Setup Ut Advanced	cility - C Chipset	Copyright (C Security	) 2018 A Boot	American Save	n Megatrends, Inc. & Exit
> >	System PCH-IO	Agent (SA) Configurati	Configura	ation			System Agent (SA) Parameters →←: Select Screen ↑↓: Select Item Enter: Select
							+/-: Change Opt. F1: General Help F2: Previous Values
							F3: Optimized Defaults F4: Save & Exit ESC: Exit
	V	ersion 2.20	.1271. Co	pyright (C)	2018 Ame	erican	Megatrends, Inc.

**BIOS Menu 12: Chipset** 





## 4.4.1 System Agent (SA) Configuration

Use the **System Agent (SA) Configuration** menu (**BIOS Menu 13**) to configure the System Agent (SA) parameters.

Aptio Setup Utility - Copy Chipset	right (C) 2018 America	n Megatrends, Inc.
System Agent (SA) Configuration		VT-d capability
VT-d VT-d	Supported [Enabled]	→←: Select Screen
<ul> <li>&gt; Memory Configuration</li> <li>&gt; Graphics Configuration</li> <li>&gt; PEG Port Configuration</li> </ul>		<pre>↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271. Copyr:	ight (C) 2018 American	Megatrends, Inc.

BIOS Menu 13: System Agent (SA) Configuration

#### → VT-d [Enabled]

Use the VT-d option to enable or disable VT-d capability.

→	Disabled	Disables VT-d capability.
-		

Enabled DEFAULT Enables VT-d capability.





## 4.4.1.1 Memory Configuration

Use the Memory Configuration submenu (BIOS Menu 14) to view memory information.

Aptio Setup Utility - ( Chipset	Copyright (C) 2018 America	n Megatrends, Inc.
Memory Configuration CHA_DIMMO Size Number of Ranks Manufacturer CHB_DIMMO Size Number of Ranks Manufacturer	Populated & Enabled 4096 MB (DDR4) 1 Unknown Populated & Enabled 4096 MB (DDR4) 1 Unknown	<pre>→←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271. Co	pyright (C) 2018 American	Megatrends, Inc.

**BIOS Menu 14: Memory Configuration** 

## 4.4.1.2 Graphics Configuration

Use the **Graphics Configuration** (**BIOS Menu 15**) menu to configure the video device connected to the system.

Aptio Setup Utility - C Chipset	opyright (C) 2018 An	merican Megatrends, Inc.
Graphics Configuration Primary Display Internal Graphics DVMT Pre-Allocated DVMT Total Gfx Mem	[Auto] [Enabled] [32M] [MAX]	Select which of IGFX/PEG/PCI Graphics device should be Primary Display. → ←: Select Screen ↑ ↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit
Version 2.20.1271. Cop	pyright (C) 2018 Ame	erican Megatrends, Inc.

**BIOS Menu 15: Graphics Configuration** 

Page 48

#### → Primary Display [Auto]

Use the **Primary Display** option to select the primary graphics controller the system uses. The following options are available:

- Auto
   Default
- IGFX
- PEG
- PCle

#### → Internal Graphics [Enabled]

Use the **Internal Graphics** option to keep IGFX enabled basing on the setup options. The following options are available:

- Auto
- Disabled
- Enabled Default

#### → DVMT Pre-Allocated [32M]

Use the **DVMT Pre-Allocated** option to set the amount of system memory allocated to the integrated graphics processor when the system boots. The system memory allocated can then only be used as graphics memory, and is no longer available to applications or the operating system. Configuration options are listed below:

- 32M Default
- 64M

#### → DVMT Total Gfx Mem [MAX]

Use the **DVMT Total Gfx Mem** option to select DVMT5.0 total graphic memory size used by the internal graphic device. The following options are available:

- 128M
- 256M
- MAX Default





## 4.4.1.3 PEG Port Configuration

Aptio Setup Utility - Copy Chipset	right (C) 2018 Ameri	lcan Megatrends, Inc.
PEG Port Configuration PCIEx16	Not Present	Enable or Disable the Root Port
Enable Root Port Max Link Speed	[Enabled] [Auto]	→←: Select Screen ↓: Select Item
> PEG Port Feature Configuration	L	Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit
Version 2.20.1271. Copyr:	ight (C) 2018 Americ	an Megatrends, Inc.

**BIOS Menu 16: PEG Port Configuration** 

#### → Enable Root Port [Enabled]

Use the Enable Root Port option to enable or disable the PCI Express (PEG) controller.

→	Disabled		Disables the PCI Express (PEG) controller.
→	Enabled	DEFAULT	Enables the PCI Express (PEG) controller.

#### → Max Link Speed [Auto]

Use the **Max Link Speed** option to select the maximum link speed of the PCI Express slot. The following options are available:

- Auto **Default**
- Gen1
- Gen2
- Gen3





# 4.4.2 PCH-IO Configuration

Use the PCH-IO Configuration menu (BIOS Menu 17) to configure the PCH parameters.

Aptio Setup Utility - Copy Chipset	yright (C) 2018 America	n Megatrends, Inc.
PCH-IO Configuration Auto Power Button Status Restore AC Power Loss	[Disable (ATX)] [Last State]	Select AC power state when power is re-applied after a power failure.
> SATA And RST Configuration > HD Audio Configuration		<pre>→ ←: Select Screen ↑ ↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271. Copyr	right (C) 2018 American	Megatrends, Inc.

**BIOS Menu 17: PCH-IO Configuration** 

#### → Restore AC Power Loss [Last State]

Use the **Restore AC Power Loss** BIOS option to specify what state the system returns to if there is a sudden loss of power to the system.

→	Power Off		The system remains turned off
→	Power On		The system turns on
→	Last State	DEFAULT	The system returns to its previous state. If it was on, it
			turns itself on. If it was off, it remains off.



## 4.4.2.1 SATA and RST Configuration

Integration Corp.

Use the **SATA and RST Configuration** menu (**BIOS Menu 18**) to change and/or set the configuration of the SATA devices installed in the system.

Aptio Setup Utility - Chipse	– Copyright (C) 2018 Americ t	an Megatrends, Inc.
SATA And RST Configuration SATA Controller(s) SATA Mode Selection	[Enabled] [AHCI]	Enable/Disable SATA Device.
SATA_SLOT1 (SATA1) Hot Plug SATA_SLOT1 (SATA2) Hot Plug MINI_PCIE1 (M-SATA) M_2_BKEY1	Empty [Disabled] 256GB SATA Fla (256.0GB) [Disabled] Empty Empty	<pre>→ ←: Select Screen ↑ ↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271.	Copyright (C) 2018 America	F4: Save & Exit ESC: Exit n Megatrends, Inc.

**BIOS Menu 18: SATA and RST Configuration** 

#### → SATA Controller(s) [Enabled]

Use the SATA Controller(s) option to configure the SATA controller(s).

→	Enabled	DEFAULT	Enables the on-board SATA controller(s).
→	Disabled		Disables the on-board SATA controller(s).

#### → SATA Mode Selection [AHCI]

Use the SATA Mode Selection option to determine how the SATA devices operate.

AHCI DEFAULT Configures SATA devices as AHCI device.



#### → Hot Plug

Use the **Hot Plug** option to enable or disable the hot plug function.

<b>→</b>	Disabled	DEFAULT	Disables the hot plug function.
→	Enabled		Enables the hot plug function.

## 4.4.2.2 HD Audio Configuration

Use the **HD Audio Configuration** menu (**BIOS Menu 19**) to configure the PCH Azalia settings.

Integration Corp.

Aptio Setup Utility Chips	- Copyright (C) 2018 Ame <mark>et</mark>	rican Megatrends, Inc.
HD Audio Configuration HD Audio	[Enabled]	Control Detection of the HD-Audio device. Disable = HDA will be unconditionally disabled Enabled = HDA will be unconditionally enabled
Vergine 2, 20, 1271	(or might (C) 2019 Amount	<pre>→ ←: Select Screen ↑ ↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271.	Copyright (C) 2018 Ameri	lcan Megatrends, Inc.

**BIOS Menu 19: HD Audio Configuration** 

#### → HD Audio [Enabled]

Use the HD Audio option to enable or disable the High Definition Audio controller.

- Disabled
   The onboard High Definition Audio controller is disabled.
- Enabled DEFAULT The onboard High Definition Audio controller is enabled.





# 4.5 Security

Use the Security menu (BIOS Menu 20) to set system and user passwords.

MainAdvancedChipsetSecurityBootSave & ExitPasswordDescriptionSet Administrator PasswordSet Administrator PasswordIf ONLY the Administrator's password is set,Set Administrator	
Password Description Set Administrator If ONLY the Administrator's password is set,	
If ONLY the Administrator's password is set,	
then this only limits access to Setup and is only asked for when entering Setup. If ONLY the User's password is set, then this	
<pre>is a power on password and must be entered to boot or enter Setup. In Setup the User will have Administrator rights. The password length must be: Minimum length</pre>	es ults
Administrator Password F4: Save & Exit User Password ESC: Exit	

**BIOS Menu 20: Security** 

#### ➔ Administrator Password

Use the Administrator Password to set or change a administrator password.

#### ➔ User Password

Use the **User Password** to set or change a user password.

## 4.6 Boot

Use the Boot menu (BIOS Menu 21) to configure system boot options.

Aptio Setup Utility - Main Advanced Chipse	- Copyright (C) 2018 America t Security <mark>Boot</mark> Save	n Megatrends, Inc. & Exit
Boot Configuration Bootup NumLock State Quiet Boot	[On] [Enabled]	Select the keyboard NumLock state
UEFI Boot Launch PXE OpROM Option ROM Messages Boot Option Priorities	[Disabled] [Disabled] [Force BIOS]	<pre>→←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help</pre>
Hard Drive BBS Priorities	[P0: 2506B SATA FIASH Drive]	F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit
Version 2.20.1271.	Copyright (C) 2018 American	Megatrends, Inc.

BIOS Menu 21: Boot

#### ➔ Bootup NumLock State [On]

Use the **Bootup NumLock State** BIOS option to specify if the number lock setting must be modified during boot up.

<b>→</b>	On	DEFAULT	Allows the Number Lock on the keyboard to be
			enabled automatically when the computer system
			boots up. This allows the immediate use of the
			10-key numeric keypad located on the right side of
			the keyboard. To confirm this, the Number Lock LED
			light on the keyboard is lit.
_			

Off Does not enable the keyboard Number Lock automatically. To use the 10-keys on the keyboard, press the Number Lock key located on the upper left-hand corner of the 10-key pad. The Number Lock LED on the keyboard lights up when the Number Lock is engaged.

# El Integration Corp.

## PUZZLE-IN002

#### Quiet Boot [Enabled]

Use the **Quiet Boot** BIOS option to select the screen display when the system boots.

→	Disabled		Normal POST messages displayed	
→	Enabled	DEFAULT	OEM Logo displayed instead of POST messages	

#### → UEFI Boot [Disabled]

Use the **UEFI Boot** option to enable or disable to boot from the UEFI devices.

→	Disabled	DEFAULT	Boot from UEFI devices is disabled.
→	Enabled		Boot from UEFI devices is enabled.

#### → Launch PXE OpROM [Disabled]

Use the **Launch PXE OpROM** option to enable or disable boot option for legacy network devices.

→	Disabled	DEFAULT	Ignore all PXE Option ROMs
---	----------	---------	----------------------------

➔ Enabled Load PXE Option ROMs.

→ Option ROM Messages [Force BIOS]

Use the **Option ROM Messages** option to set the Option ROM display mode.

Force DEFAULT Sets display mode to force BIOS.
 BIOS

Keep Sets display mode to current.
 Current



## 4.7 Save & Exit

Use the **Safe & Exit** menu (**BIOS Menu 22**) to load default BIOS values, optimal failsafe values and to save configuration changes.

Integration Corp.

Page 57

Aptio Setup Utility - Copyright (C) 2018 America Main Advanced Chipset Security Boot <mark>Save</mark>	n Megatrends, Inc. & Exit
Save Changes and Reset Discard Changes and Reset	Exit the system after saving the changes.
Restore Defaults Save as User Defaults Restore User Defaults	<pre>→←: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save &amp; Exit ESC: Exit</pre>
Version 2.20.1271. Copyright (C) 2018 American	Megatrends, Inc.

BIOS Menu 22: Save & Exit

#### → Save Changes and Reset

Use the **Save Changes and Reset** option to save the changes made to the BIOS options and reset the system.

#### → Discard Changes and Reset

Use the **Discard Changes and Reset** option to exit the system without saving the changes made to the BIOS configuration setup program.

#### → Restore Defaults

Use the **Restore Defaults** option to load the optimal default values for each of the parameters on the Setup menus. **F3 key can be used for this operation.** 

#### → Save as User Defaults

Use the **Save as User Defaults** option to save the changes done so far as user defaults.

#### → Restore User Defaults

Use the **Restore User Defaults** option to restore the user defaults to all the setup options.





# **Interface Connectors**

Page 58

# **5.1 Peripheral Interface Connectors**

The connector locations of the PUZZLE-IN002's motherboard are shown below. The connector pinouts for these connectors are listed in the following sections.





# **5.2 Internal Peripheral Connectors**

The table below shows a list of the connectors on the motherboard. Pinouts of these connectors can be found in the following sections.

Connector	Туре	Label
ATX power connector	24-pin connector	ATX1
CPU power connector	4-pin connector	CPU12V1
Chassis intrusion connector	2-pin header	CHASSIS1
Digital I/O connector	10-pin header	DIO1
EC debug connector	18-pin header	CN1
Fan connectors	4-pin wafer	CPU_FAN1, CPU_FAN2,
		CPU_FAN3, SYS_FAN1
Front panel connector	14-pin header	F_PANEL1
LCM connector	8-pin wafer	CN2
M.2 slot	M.2 A-key slot	M2_CN1
Memory slots	DDR4 DIMM slot	CHA_DIMM0,
		CHB_DIMM0
Mini-SATA slot (full-/half-size)	Mini-SATA slot	MINI_PCIE1
Power switch connector	2-pin wafer	PWR_BTN1
Power button (on-board)	Push button	PWR_SW1
SATA 6Gb/s socket	36-pin socket	SATA_SLOT1
SIM card slot	SIM card slot	SIM1
SPI flash connector	6-pin wafer	JSPI1
SPI flash connector (EC)	6-pin wafer	JSPI2
TPM connector	20-pin header	TPM1
USB 2.0 connector	8-pin header	USB1
USB DOM connector	8-pin header	USB_DOM1

**Table 5-1: Peripheral Interface Connectors** 

## 5.2.1 ATX Power Connector (ATX1)

Pin	Description	Pin	Description
1	+3.3 V	13	+3.3 V
2	+3.3 V	14	-12 V
3	GND	15	GND
4	+5 V	16	PS-ON
5	GND	17	GND
6	+5 V	18	GND
7	GND	19	GND
8	PW-OK	20	N/C
9	+5VSB	21	+5 V
10	+12V	22	+5 V
11	+12V	23	+5 V
12	+3.3 V	24	GND

Table 5-2: ATX Power Connector Pinouts

## 5.2.2 CPU Power Connector (CPU12V1)

Pin	Description	
1	GND	
2	GND	
3	+12 V	
4	+12 V	

Table 5-3: CPU Power Connector (CPU12V1) Pinouts

## 5.2.3 Chassis Intrusion Connector (CHASSIS1)

PIN NO.	DESCRIPTION	
1	+3.3VSB	
2	CHASSIS OPEN	

 Table 5-4: Chassis Intrusion Connector (CHASSIS1) Pinouts



## 5.2.4 DIO Connector (DIO1)

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION	
1	GND	2	VCC	10 9
3	Output 3	4	Output 2	
5	Output 1	6	Output 0	
7	Input 3	8	Input 2	2 0 0 1
9	Input 1	10	Input 0	

Table 5-5: DIO Connector (DIO1) Pinouts

## 5.2.5 EC Debug Connector (CN1)

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	EC_EPP_STB#	2	EC_EPP_AFD#
3	EC_EPP_PD0	4	NC
5	EC_EPP_PD1	6	EC_EPP_INIT#
7	EC_EPP_PD2	8	EC_EPP_SLIN#
9	EC_EPP_PD3	10	GND
11	EC_EPP_PD4	12	NC
13	EC_EPP_PD5	14	EC_EPP_BUSY
15	EC_EPP_PD6	16	EC_EPP_KSI5
17	EC_EPP_PD7	18	EC_EPP_KSI4

Table 5-6: EC Debug Connector (CN1) Pinouts

## 5.2.6 Fan Connectors (CPU\_FAN1/2/3, SYS\_FAN1)

PIN NO.	DESCRIPTION
1	GND
2	+12V
3	FANIO
4	PWM



Page 62
# 5.2.7 Front Panel Connector (F\_PANEL1)

FUNCTION	PIN	DESCRIPTION	FUNCTION	PIN	DESCRIPTION
Power LED	1	PWR_LED+	Speaker	2	Speaker+
	3	N/C		4	N/C
	5	PWR_LED-		6	N/C
Power Button	7	PWR_BTN+		8	Speaker-
	9	PWR_BTN-	Reset	10	N/C
HDD LED	11	HDD LED+		12	Reset+
	13	HDD LED-		14	Reset-

Table 5-8: Front Panel Connector (F\_PANEL1) Pinouts

# 5.2.8 LCM Connector (CN2)

PIN NO.	DESCRIPTION
1	VCC5V
2	Power button
3	LCM RX
4	LCM TX
5	HDD LED
6	Alert LED
7	Reset button
8	GND

Table 5-9: LCM Connector (CN2) Pinouts



# 5.2.1 M.2 Slot (M2\_CN1)

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	GND	2	+3.3V
3	USB_D+	4	+3.3V
5	USB_D-	6	N/C
7	GND	8	N/C
9	N/C	10	N/C
11	N/C	12	N/C
13	N/C	14	N/C
15	N/C	16	N/C
17	N/C	18	GND
19	N/C	20	N/C
21	N/C	22	N/C
23	N/C	24	N/C
25	N/C	26	N/C
27	N/C	28	N/C
29	N/C	30	N/C
31	N/C	32	N/C
33	GND	34	N/C
35	PCIe_TX+	36	N/C
37	PCIe_TX-	38	N/C
39	GND	40	N/C
41	PCIe_RX+	42	N/C
43	PCIe_RX-	44	N/C
45	GND	46	N/C
47	REFCLK+	48	N/C
49	REFCLK-	50	PCH_SUSCLK
51	GND	52	RST
53	CLKREQ	54	BT_RF_KILL-
55	PCH_WAKE-	56	WIFI_RF_KILL-
57	GND	58	I2C_DATA
59	N/C	60	I2C_CLK

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
61	N/C	62	INT-
63	GND	64	N/C
65	N/C	66	RESET-
67	N/C	68	CLKREQ
69	GND	70	PEWAKE-
71	N/C	72	+3.3V
73	N/C	74	+3.3V
75	GND		

Table 5-10: M.2 Slot (M2\_CN1) Pinouts

# 5.2.2 Mini-SATA Card Slot (MINI\_PCIE1)

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	PCH_WAKE-	2	+3.3V
3	N/C	4	GND
5	N/C	6	1.5V
7	N/C	8	SIM_VCC
9	GND	10	SIM_IO
11	MSATA_CLK-	12	SIM_CLK
13	MSATA _CLK+	14	SIM_RST
15	GND	16	SIM_VPP
17	PLTRST_N	18	GND
19	N/C	20	+3.3V
21	GND	22	PLTRST_N
23	SATA_RX+	24	+3.3V
25	SATA_RX-	26	GND
27	GND	28	1.5V
29	GND	30	SMB_CLK
31	SATA_TX-	32	SMB_DATA
33	SATA_TX+	34	GND
35	GND	36	USB_DATA-

Page 65

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
37	GND	38	USB_DATA+
39	+3.3V	40	GND
41	+3.3V	42	N/C
43	GND	44	RF_LINK#
45	N/C	46	BLUELED#
47	N/C	48	1.5V
49	N/C	50	GND
51	N/C	52	+3.3V

#### Table 5-11: Mini-SATA Card Slot (MINI\_PCIE1) Pinouts

# 5.2.1 Power Switch Connector (PWR\_BTN1)

PIN NO.	DESCRIPTION
1	PWRBTN_SW+
2	PWRBTN_SW-

Table 5-12: Power Switch Connector (PWR\_BTN1) Pinouts

# 5.2.2 SATA Connector (SATA\_SLOT1)

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
B1	+V12S	A1	N/C
B2	+V12S	A2	+V12S
В3	+V12S	A3	+V12S
B4	GND	A4	GND
B5	SATA_TX2-	A5	+V5S
B6	SATA_TX2+	A6	+V5S
B7	GND	A7	SATA_RX2-
B8	+V3.3S	A8	SATA RX2+
В9	+V5S	A9	+V3.3S
B10	N/C	A10	+V3.3S
B11	+V5S	A11	+V5S
B12	+V5S	A12	GND

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
B13	GND	A13	N/C
B14	SATA_TX1-	A14	N/C
B15	SATA_TX1+	A15	GND
B16	GND	A16	SATA_RX1-
B17	+V5S	A17	SATA RX1+
B18	GND	A18	GND

#### Table 5-13: SATA 6Gb/s Connector (SATA\_SLOT1) Pinouts

## 5.2.3 SPI Flash Connector (JSPI1)

PIN NO.	DESCRIPTION
1	+1.8V
2	SPI_CS
3	SPI_SO
4	SPI_CLK
5	SPI_SI
6	GND

Table 5-14: SPI Flash Connector (JSPI1) Pinouts

## 5.2.4 SPI Flash Connector - EC (JSPI2)

PIN NO.	DESCRIPTION
1	+V3.3
2	SPI_CS#0_CN_EC
3	SPI_SO_SW_EC
4	SPI_CLK_SW_EC
5	SPI_SI_SW_EC
6	GND

Table 5-15: SPI Flash Connector - EC (JSPI2) Pinouts



# 5.2.5 TPM Connector (TPM1)

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	LCLK	2	GND
3	LFRAME#	4	KEY
5	LRERST#	6	+5V
7	LAD3	8	LAD2
9	+3.3V	10	LAD1
11	LADO	12	GND
13	SCL	14	SDA
15	SB3V	16	SERIRQ
17	GND	18	GLKRUN#
19	LPCPD#	20	LDRQ#

Table 5-16: TPM Connector (TPM1) Pinouts

# 5.2.6 USB 2.0 Connector (USB1)

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION	
1	VCC	2	GND	8 • • 7
3	USB_DATA-	4	USB_DATA+	
5	USB_DATA+	6	USB_DATA-	2 • • 1
7	GND	8	VCC	

Table 5-17: USB 2.0 Connector (USB1) Pinouts

# 5.2.7 USB DOM Connector (USB\_DOM1)

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION	
1	VCC5V	2	N/A	8 • • 7
3	USB-	4	N/A	
5	USB+	6	N/A	2 • • 1
7	GND	8	N/A	



Table 5-18: USB DOM Connector (USB\_DOM1) Pinouts

F







# **Regulatory Compliance**

#### DECLARATION OF CONFORMITY

# CE

Integration Corp.

This equipment is in conformity with the following EU directives:

- EMC Directive 2014/30/EU
- Low-Voltage Directive 2014/35/EU
- RoHS II Directive 2011/65/EU

If the user modifies and/or install other devices in the equipment, the CE conformity declaration may no longer apply.

If this equipment has telecommunications functionality, it also complies with the requirements of the R&TTE Directive 1999/5/EC.

#### English

IEI Integration Corp declares that this equipment is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC.

Български [Bulgarian]

IEI Integration Corp. декларира, че този оборудване е в съответствие със

съществените изисквания и другите приложими правила на Директива 1999/5/EC.

Česky [Czech]

IEI Integration Corp tímto prohlašuje, že tento zařízení je ve shodě se základními požadavky a dalšími příslušnými ustanoveními směrnice 1999/5/ES.

Dansk [Danish]

IEI Integration Corp erklærer herved, at følgende udstyr overholder de væsentlige krav og øvrige relevante krav i direktiv 1999/5/EF.

Deutsch [German]

IEI Integration Corp, erklärt dieses Gerät entspricht den grundlegenden Anforderungen und den weiteren entsprechenden Vorgaben der Richtlinie 1999/5/EU.

Eesti [Estonian]

IEI Integration Corp deklareerib seadme seadme vastavust direktiivi 1999/5/EÜ

põhinõuetele ja nimetatud direktiivist tulenevatele teistele asjakohastele sätetele.

Español [Spanish]

IEI Integration Corp declara que el equipo cumple con los requisitos esenciales y cualesquiera otras disposiciones aplicables o exigibles de la Directiva 1999/5/CE.

Ελληνική [Greek]

ΙΕΙ Integration Corp ΔΗΛΩΝΕΙ ΟΤΙ ΕΞΟΠΛΙΣΜΟΣ ΣΥΜΜΟΡΦΩΝΕΤΑΙ ΠΡΟΣ ΤΙΣ ΟΥΣΙΩΔΕΙΣ ΑΠΑΙΤΗΣΕΙΣ ΚΑΙ ΤΙΣ ΛΟΙΠΕΣ ΣΧΕΤΙΚΕΣ ΔΙΑΤΑΞΕΙΣ ΤΗΣ ΟΔΗΓΙΑΣ 1999/5/ΕΚ.

Français [French]

IEI Integration Corp déclare que l'appareil est conforme aux exigences essentielles et aux autres dispositions pertinentes de la directive 1999/5/CE.

Italiano [Italian]

IEI Integration Corp dichiara che questo apparecchio è conforme ai requisiti essenziali ed alle altre disposizioni pertinenti stabilite dalla direttiva 1999/5/CE.

Latviski [Latvian]

IEI Integration Corp deklarē, ka iekārta atbilst būtiskajām prasībām un citiem ar to saistītajiem noteikumiem Direktīvas 1999/5/EK.

Lietuvių [Lithuanian]

IEI Integration Corp deklaruoja, kad šis įranga atitinka esminius reikalavimus ir kitas

1999/5/EB Direktyvos nuostatas.

Nederlands [Dutch]

IEI Integration Corp dat het toestel toestel in overeenstemming is met de essentiële eisen en de andere relevante bepalingen van richtlijn 1999/5/EG.

Malti [Maltese]

IEI Integration Corp jiddikjara li dan prodott jikkonforma mal-ħtiġijiet essenzjali u ma provvedimenti oħrajn relevanti li hemm fid-Dirrettiva 1999/5/EC.

Magyar [Hungarian]

IEI Integration Corp nyilatkozom, hogy a berendezés megfelel a vonatkozó alapvető

követelményeknek és az 1999/5/EC irányelv egyéb előírásainak.

Polski [Polish]

IEI Integration Corp oświadcza, że wyrobu jest zgodny z zasadniczymi wymogami oraz pozostałymi stosownymi postanowieniami Dyrektywy 1999/5/EC.

Português [Portuguese]

IEI Integration Corp declara que este equipamento está conforme com os requisitos essenciais e outras disposições da Directiva 1999/5/CE.

Româna [Romanian]

IEI Integration Corp declară că acest echipament este in conformitate cu cerințele

esențiale și cu celelalte prevederi relevante ale Directivei 1999/5/CE.

Slovensko [Slovenian]

IEI Integration Corp izjavlja, da je ta opreme v skladu z bistvenimi zahtevami in ostalimi relevantnimi določili direktive 1999/5/ES.

Slovensky [Slovak]

IEI Integration Corp týmto vyhlasuje, že zariadenia spĺňa základné požiadavky a všetky príslušné ustanovenia Smernice 1999/5/ES.

Suomi [Finnish]

IEI Integration Corp vakuuttaa täten että laitteet on direktiivin 1999/5/EY oleellisten

vaatimusten ja sitä koskevien direktiivin muiden ehtojen mukainen.

Svenska [Swedish]

IEI Integration Corp förklarar att denna utrustningstyp står I överensstämmelse med de väsentliga egenskapskrav och övriga relevanta bestämmelser som framgår av direktiv 1999/5/EG.



### FCC WARNING

Integration Corp.



This equipment complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- This device may not cause harmful interference, and
- This device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

#### **ROHS STATEMENT**



The label on the product indicates this product conforms to European (EU) Restriction of Hazardous Substances (RoHS) that set maximum concentration limits on hazardous materials used in electrical and electronic equipment.

#### **CHINA ROHS**



The label on the product indicates the estimated "Environmentally Friendly Use Period" (EFUP). This is an estimate of the number of years that these substances would "not leak out or undergo abrupt change." This product may contain replaceable sub-assemblies/components which have a shorter EFUP such as batteries and lamps. These components will be separately marked.



EnIntegration Corp.

# **Safety Precautions**



## **B.1 Safety Precautions**

# 🖄 WARNING:

The precautions outlined in this appendix should be strictly followed. Failure to follow these precautions may result in permanent damage to the PUZZLE-IN002.

Please follow the safety precautions outlined in the sections that follow:

#### **B.1.1 General Safety Precautions**

Please ensure the following safety precautions are adhered to at all times.

- Make sure the power is turned off and the power cord is disconnected when moving, installing or modifying the system.
- Do not apply voltage levels that exceed the specified voltage range.
  Doing so may cause fire and/or an electrical shock.
- Electric shocks can occur if opened while still powered on.
- Do not drop or insert any objects into the ventilation openings.
- If considerable amounts of dust, water, or fluids enter the system, turn off the power supply immediately, unplug the power cord, and contact the system vendor.
- DO NOT:
  - O Drop the system against a hard surface.
  - O In a site where the ambient temperature exceeds the rated temperature

#### **B.1.2 Anti-static Precautions**



Failure to take ESD precautions during the installation of the PUZZLE-IN002 may result in permanent damage to the PUZZLE-IN002 and severe injury to the user.

Electrostatic discharge (ESD) can cause serious damage to electronic components, including the PUZZLE-IN002. Dry climates are especially susceptible to ESD. It is therefore critical that whenever the PUZZLE-IN002 is opened and any of the electrical components are handled, the following anti-static precautions are strictly adhered to.

- Wear an anti-static wristband: Wearing a simple anti-static wristband can help to prevent ESD from damaging any electrical component.
- Self-grounding: Before handling any electrical component, touch any grounded conducting material. During the time the electrical component is handled, frequently touch any conducting materials that are connected to the ground.
- Use an anti-static pad: When configuring or working with an electrical component, place it on an anti-static pad. This reduces the possibility of ESD damage.
- Only handle the edges of the electrical component. When handling the electrical component, hold the electrical component by its edges.

#### **B.1.3 Product Disposal**

Risk of explosion if the battery is replaced by an incorrect type;

Dispose of used batteries according to instructions and local regulations.

- Outside the European Union If you wish to dispose of used electrical and electronic products outside the European Union, please contact your local authority so as to comply with the correct disposal method.
- Within the European Union:



EU-wide legislation, as implemented in each Member State, requires that waste electrical and electronic products carrying the mark (left) must be disposed of separately from normal household waste. This includes monitors and electrical accessories, such as signal cables or power cords. When you need to dispose of your display products, please follow



the guidance of your local authority, or ask the shop where you purchased the product. The mark on electrical and electronic products only applies to the current European Union Member States.

Please follow the national guidelines for electrical and electronic product disposal.

# **B.2 Maintenance and Cleaning Precautions**

When maintaining or cleaning the PUZZLE-IN002, please follow the guidelines below.

#### **B.2.1 Maintenance and Cleaning**

Prior to cleaning any part or component of the PUZZLE-IN002, please read the details below.

- The interior of the PUZZLE-IN002 does not require cleaning. Keep fluids away from the PUZZLE-IN002 interior.
- Be cautious of all small removable components when vacuuming the PUZZLE-IN002.
- Turn the PUZZLE-IN002 off before cleaning the PUZZLE-IN002.
- Never drop any objects or liquids through the openings of the PUZZLE-IN002.
- Be cautious of any possible allergic reactions to solvents or chemicals used when cleaning the PUZZLE-IN002.
- Avoid eating, drinking and smoking within vicinity of the PUZZLE-IN002.

#### **B.2.2 Cleaning Tools**

Some components in the PUZZLE-IN002 may only be cleaned using a product specifically designed for the purpose. In such case, the product will be explicitly mentioned in the cleaning tips. Below is a list of items to use when cleaning the PUZZLE-IN002.

- Cloth Although paper towels or tissues can be used, a soft, clean piece of cloth is recommended when cleaning the PUZZLE-IN002.
- Water or rubbing alcohol A cloth moistened with water or rubbing alcohol can be used to clean the PUZZLE-IN002.
- Using solvents The use of solvents is not recommended when cleaning the PUZZLE-IN002 as they may damage the plastic parts.



 Vacuum cleaner – Using a vacuum specifically designed for computers is one of the best methods of cleaning the PUZZLE-IN002. Dust and dirt can restrict the airflow in the PUZZLE-IN002 and cause its circuitry to corrode.

Integration Corp.

 Swabs - Swaps moistened with rubbing alcohol or water are excellent tools for wiping hard to reach areas. Whenever possible, it is best to use lint free swabs such as foam swabs for cleaning.







# Hazardous Materials Disclosure

The details provided in this appendix are to ensure that the product is compliant with the Peoples Republic of China (China) RoHS standards. The table below acknowledges the presences of small quantities of certain materials in the product, and is applicable to China RoHS only.

A label will be placed on each product to indicate the estimated "Environmentally Friendly Use Period" (EFUP). This is an estimate of the number of years that these substances would "not leak out or undergo abrupt change." This product may contain replaceable sub-assemblies/components which have a shorter EFUP such as batteries and lamps. These components will be separately marked.

Please refer to the following table.

Part Name	Toxic or Hazardous Substances and Elements					
	Lead	Mercury	Cadmium	Hexavalent	Polybrominated	Polybrominated
	(Pb)	(Hg)	(Cd)	Chromium	Biphenyls	Diphenyl Ethers
				(CR(VI))	(PBB)	(PBDE)
Housing	0	0	0	0	0	0
Display	0	0	0	0	0	0
Printed Circuit	0	0	0	0	0	0
Board						
Metal Fasteners	0	0	0	0	0	0
Cable Assembly	0	0	0	0	0	0
Fan Assembly	0	0	0	0	0	0
Power Supply	0	0	0	0	0	0
Assemblies						
Battery	0	0	0	0	0	0
O: This toxic or hazardous substance is contained in all of the homogeneous materials for the part is below the limit						
requirement in SJ/T11363-2006 (now replaced by GB/T 26572-2011).						

X: This toxic or hazardous substance is contained in at least one of the homogeneous materials for this part is above the limit requirement in SJ/T11363-2006 (now replaced by GB/T 26572-2011).



此附件旨在确保本产品符合中国 RoHS 标准。以下表格标示此产品中某有毒物质的含量符 合中国 RoHS 标准规定的限量要求。

本产品上会附有"环境友好使用期限"的标签,此期限是估算这些物质"不会有泄漏或突变"的 年限。本产品可能包含有较短的环境友好使用期限的可替换元件,像是电池或灯管,这些元 件将会单独标示出来。

部件名称	有毒有害物质或元素						
	铅	汞	镉	六价铬	多溴联苯	多溴二苯	
	(Pb)	(Hg)	(Cd)	(CR(VI))	(PBB)	醚	
						(PBDE)	
壳体	0	0	0	0	0	0	
显示	0	0	0	0	0	0	
印刷电路板	0	0	0	0	0	0	
金属螺帽	0	0	0	0	0	0	
电缆组装	0	0	0	0	0	0	
风扇组装	0	0	0	0	0	0	
电力供应组装	0	0	0	0	0	0	
电池	0	0	0	0	0	0	

O: 表示该有毒有害物质在该部件所有物质材料中的含量均在 SJ/T 11363-2006 (现由 GB/T 26572-2011 取代) 标准规定的限量要求以下。

X: 表示该有毒有害物质至少在该部件的某一均质材料中的含量超出 SJ/T 11363-2006 (现由 GB/T 26572-2011 取代)标准规定的限量要求。

